

Heavy Duty Phase Indicator/DMM

DMM with 3-phase power indicator for motors features temperature and frequency functions

Features:

- Large 3-1/2 digit display
- DCV, ACV, Capacitance, Frequency, °C/°F Temperature and Phase
- Direction of arrow on display identifies correct or incorrect wiring configuration
- Continuity beeper, Diode tests
- Built-in stand for benchtop use
- Designed for latest US and European safety standards
- Complete with protective holster, color coded test leads for phase, alligator clips, multimeter test leads, bead wire temperature probe, and 9V battery



CAT III-600V

Specifications:	Range	Accuracy (%rdg+digits)
DC Voltage:	2V, 20V, 200V, 600V	±(1.2% +1d)
AC Voltage:	200V, 600V	±(2.9% +4d)
Capacitance:	20μ, 200μF, 2000μF, 20mF	±(4% +10d)
Resistance (Ω):	200, 2K, 20K, 200K, 2000K, 20M, 200M, 2000M	±1%
Frequency:	10Hz to 100KHz (autoranging)	±0.5%
Temperature:	-4 to 752°F (-20 to 400°C)	±2%
Phase Indicator:	45 to 450Hz, 80 to 480VAC	
Dimensions:	5.7x2.7x1.5"(145x69x38mm) with holster	
Weight:	12oz (340g)	



Ordering Information:

380224.....Heavy Duty Phase Indicator/MultiMeter
380224-NIST..Heavy Duty Phase Indicator/MultiMeter w/NIST Certificate
380995.....Vinyl Pouch Carrying Case