

# MultiMeter Light Adaptor

Measures Foot Candle or Lux on your multimeter

## Features:

- Two models measure either in Fc (0 to 5,000Fc) or Lux (0 to 50,000Lux) with three selectable measuring ranges
- Photo diode sensor prolongs life and enables instrument to cover wide ranges
- Banana plugs insert directly into your multimeter, switch to 200mV range and aim sensor for reading on your multimeter
- Complete with 9V battery



### Specifications for both models

Fc Ranges (res.):	0 to 200Fc (0.1)	200 to 2000Fc (1)	2000 to 5000Fc (10)
Output:	1mV/Fc	0.1mV/1Fc	0.1mV/10Fc
Lux Ranges (res.):	0 to 2000Lux (1)	2000 to 20,000Lux (10)	20,000 to 50,000Lux (100)
Output:	0.1mV/1Lux	0.1mV/10Lux	0.1mV/100Lux
Accuracy:	±(5% + 0.1mV)		
Dimensions/Weight:	3.9 x 2 x 1" (100 x 50 x 25mm)/ 6.7oz (190g)		

## Ordering Information:

**401021**.....Foot Candle Adaptor  
**401020**.....Lux Adaptor  
**409992**.....Carrying Case